

**Parameters**

Wattage	24 W	36W	48W
No of LED	18	24	36
Make	Osram/Seoul	Osram/Seoul	Osram/Seoul
Power per LED	1.2 Watt	1.2 Watt	1.2 Watt
Driver Efficiency	> 85%	> 85%	> 85%
Power Factor	>.90	>.90	>.90
Input Frequency	50 Hz	50 Hz	50 Hz
CRI	>85	>85	>85
Control Circuit	PWM Type, Constant Current LED Driver	PWM Type, Constant Current LED Driver	PWM Type, Constant Current LED Driver
LED Junction Temperature	< 120Degree	< 120Degree	< 120Degree
IP Level	IP 60	IP 60	IP 60
Beam Angle of Luminaire	170Degree	170Degree	170Degree



Length = 600 mm  
Breadth = 600 mm  
Height = 30 mm



**GEARS Energy Solutions Private Limited,**

H-724 Sitapura Industrial Area, Jaipur.

Email – [info@gearsenergy.com](mailto:info@gearsenergy.com)

Contact No -0141-2771933

Mobile No - 9462784718

Website – [www.gearsenergy.com](http://www.gearsenergy.com), [www.gearslab.com](http://www.gearslab.com)

